

## SF56

*No Clean Halogen Free Liquid Flux  
For Solar Photovoltaic Application*



### Product Description

SF56 is an excellent flux to apply on solar (PV) cell bus strips prior to soldering tab ribbons in place. SF56 solder flux facilitates solder wetting by dissolving the oxides present on the surface of the tabbing ribbon as well as the silver metallization bonding stripes on the top and bottom of the solar cell. The flux flows smoothly and evenly for consistently secure and uniform solder connections with no mess. It speeds up assembly time and makes nice-looking panels. Rosin residue is non-corrosive, non-conductive, moisture resistant, and fungus resistant. There is no surface insulation resistance degradation caused by the flux residue

### Application

SF56 is formulated for the solar photovoltaic process both in SnPb and Lead Free applications. It can be applied by soaking, dipping and spraying.

Fluxing Method:

#### a) Soaking

It is recommended to soak the tab ribbon in the flux for about 4 - 8 minutes and dry it naturally in air or bake it directly in the oven until it is semi-dry.

#### b) Dipping

SF56 can also be applied by dipping the tab ribbon in the flux tank, which is carried by a conveyor.

#### c) Spraying

Ensure flux is only applied to those areas being soldered. Care should be taken to avoid overspray. Clean the nozzle head every 4 hours to prevent clogging.

Due to low efficiency, brushing method is not recommended.

Soldering Method:

#### a) Manual Soldering

After soaking the tab ribbon and dry it until semi-dry, manual solder at 320 - 380°C.

#### b) Auto-soldering

Preheat the tab ribbon that is dipped or sprayed at 50 - 130°C. The tab ribbon is then soldered by laser beam, infra-red, electromagnetic or hot air auto-heating method.

Recommended soldering temperature is 180 - 300°C.

### Specification

Item	Result
State	Liquid
Colour	Colourless
Specific Gravity @ 25°C	0.790 +/- 0.005
JIS Z 3197 8.2.2	
Non-volatile Solid Content (110°C, 1hr)	1.35 +/- 0.2 wt%
IPC-TM-650 2.3.34	
JIS Z 3197 8.1.3	
Halide Content	Not detected
JIS Z 3197 8.1.4.2.1	
Halogen Content	Not detected
BS EN 14582	
Acid Value Test	14.0 +/- 1 mg KOH/g flux
IPC-TM-650 2.3.13	
JIS Z 3197 8.1.4.1	
Water Extract Resistivity	> 1 x 10 <sup>4</sup> Ω-cm
JIS Z 3197 8.1.1	
Surface Insulation Resistance (85°C, 85%RH, 168hrs)	> 1 x 10 <sup>8</sup> Ω, Pass > 1 x 10 <sup>11</sup> Ω, Pass
IPC-TM-650 2.6.3.3	
JIS Z 3197 8.5.3	
Electromigration (85°C, 88.5%RH, 596hrs)	Pass
IPC-TM-650 2.6.14.1	
Copper Corrosion Test	Pass
IPC-TM-650 2.6.15	
JIS Z 3197 8.4.1	
Copper Mirror Test	Classified as "M", Pass
IPC-TM-650 2.3.32	
JIS Z 3197 8.4.2	
Spread Factor	> 87% (SnPb)
JIS Z 3197 8.3.1.1	
Flux Activity Classification	ROM0
IPC J-STD-004	

## SF56 No Clean Liquid Flux (For Solar Photovoltaic Application)

### Residue Removal

Since the residues are minimal and non-corrosive, removal is usually not required. If cleaning is required, the flux residue could be removed by any solvent or aqueous flux cleaner available in the market.

### Recommended Solvent

Asahi's complementary Solvent #2000. Solvent can be stored for about 2 years under normal storage conditions of 25°C.

### Health and Safety

Observe standard precautions for handling and use, such as well-ventilated areas and avoidance of prolonged or repeated contact with the skin. For more information, please refer to the Material Safety Data Sheet.

### Storage

Under proper storage condition, SF56 can be stored for up to 6 months. SF56 is flammable. Keep away from all sources of heat, sparks, flame and sunlight.

### Packaging

Available in 18kg/carboy.

#### DISCLAIMER OF LIABILITY

"All statements, information and recommendations contained in this catalog are based on data and test results which we consider, to the best of our knowledge and belief, to be reliable and informative to the users but the accuracy and completeness thereof is not guaranteed. No warranty, expressed or implied, statutory or otherwise, is given regarding the use of the information and products contained in this catalog since the conditions and suitability for use, handlings, storage or possession of the products are determined by the users and are therefore beyond our control. We shall not be liable in respect of any liabilities, losses (including consequential losses), damages, proceedings, costs, claims or injuries whatsoever sustained or suffered by the users (including any third parties) in connection with the use of the information, recommendation and the products contained in this catalog."

### Singapore Asahi Chemical and Solder Industries Pte Ltd

47 Pandan Road Singapore 609288

Tel: +65 6262-1616 Fax: +65 6261-6311

Website: <http://www.asahisolder.com> Email: [enquiry@sinasahi.com.sg](mailto:enquiry@sinasahi.com.sg)