




- ▼ Lower On-resistance
- ▼ Simple Drive Requirement
- ▼ Fast Switching Characteristic
- ▼ RoHS Compliant & Halogen-Free




$BV_{DSS}$	-40V
$R_{DS(ON)}$	16mΩ
$I_D$	-45A

## Description

XP9561 series are innovative design and silicon process technology to achieve the lowest possible on-resistance and fast switching performance. It provides the designer with an extreme efficient device for use in a wide range of power applications.

The TO-252 package is widely preferred for all commercial-industrial surface mount applications using infrared reflow technique and suited for high current application due to the low connection resistance.



## Absolute Maximum Ratings@ $T_j=25^\circ\text{C}$ (unless otherwise specified)

Symbol	Parameter	Rating	Units
$V_{DS}$	Drain-Source Voltage	-40	V
$V_{GS}$	Gate-Source Voltage	$\pm 20$	V
$I_D @ T_C = 25^\circ\text{C}$	Drain Current, $V_{GS} @ 10\text{V}$	-45	A
$I_D @ T_C = 100^\circ\text{C}$	Drain Current, $V_{GS} @ 10\text{V}$	-29	A
$I_{DM}$	Pulsed Drain Current <sup>1</sup>	-180	A
$P_D @ T_C = 25^\circ\text{C}$	Total Power Dissipation	54.3	W
$T_{STG}$	Storage Temperature Range	-55 to 150	°C
$T_J$	Operating Junction Temperature Range	-55 to 150	°C

## Thermal Data

Symbol	Parameter	Value	Units
$R_{thj-c}$	Maximum Thermal Resistance Junction-case	2.3	°C/W
$R_{thj-a}$	Maximum Thermal Resistance, Junction-ambient (PCB mount) <sup>3</sup>	62.5	°C/W
$R_{thj-a}$	Maximum Thermal Resistance Junction-ambient	110	°C/W

### Electrical Characteristics@ $T_j=25^\circ\text{C}$ (unless otherwise specified)

Symbol	Parameter	Test Conditions	Min.	Typ.	Max.	Units
$\text{BV}_{\text{DSS}}$	Drain-Source Breakdown Voltage	$V_{\text{GS}}=0\text{V}, I_{\text{D}}=-250\mu\text{A}$	-40	-	-	V
$R_{\text{DS}(\text{ON})}$	Static Drain-Source On-Resistance <sup>2</sup>	$V_{\text{GS}}=-10\text{V}, I_{\text{D}}=-30\text{A}$	-	-	16	$\text{m}\Omega$
		$V_{\text{GS}}=-4.5\text{V}, I_{\text{D}}=-20\text{A}$	-	-	28	$\text{m}\Omega$
$V_{\text{GS}(\text{th})}$	Gate Threshold Voltage	$V_{\text{DS}}=V_{\text{GS}}, I_{\text{D}}=-250\mu\text{A}$	-1	-	-3	V
$g_{\text{fs}}$	Forward Transconductance	$V_{\text{DS}}=-10\text{V}, I_{\text{D}}=-20\text{A}$	-	33	-	S
$I_{\text{DSS}}$	Drain-Source Leakage Current	$V_{\text{DS}}=-32\text{V}, V_{\text{GS}}=0\text{V}$	-	-	-10	$\text{uA}$
	Drain-Source Leakage Current ( $T_j=125^\circ\text{C}$ )	$V_{\text{DS}}=-32\text{V}, V_{\text{GS}}=0\text{V}$	-	-	-250	$\text{uA}$
$I_{\text{GSS}}$	Gate-Source Leakage	$V_{\text{GS}}=\pm 20\text{V}, V_{\text{DS}}=0\text{V}$	-	-	$\pm 100$	$\text{nA}$
$Q_g$	Total Gate Charge <sup>2</sup>	$I_{\text{D}}=-20\text{A}$	-	25	40	$\text{nC}$
$Q_{\text{gs}}$	Gate-Source Charge	$V_{\text{DS}}=-32\text{V}$	-	4.4	-	$\text{nC}$
$Q_{\text{gd}}$	Gate-Drain ("Miller") Charge	$V_{\text{GS}}=-4.5\text{V}$	-	18	-	$\text{nC}$
$t_{\text{d}(\text{on})}$	Turn-on Delay Time <sup>2</sup>	$V_{\text{DS}}=-20\text{V}$	-	9	-	ns
$t_r$	Rise Time	$I_{\text{D}}=-20\text{A}$	-	46	-	ns
$t_{\text{d}(\text{off})}$	Turn-off Delay Time	$R_{\text{G}}=3.3\Omega$	-	46	-	ns
$t_f$	Fall Time	$V_{\text{GS}}=-10\text{V}$	-	95	-	ns
$C_{\text{iss}}$	Input Capacitance	$V_{\text{GS}}=0\text{V}$	-	1700	2720	$\text{pF}$
$C_{\text{oss}}$	Output Capacitance	$V_{\text{DS}}=-25\text{V}$	-	360	-	$\text{pF}$
$C_{\text{rss}}$	Reverse Transfer Capacitance	f=1.0MHz	-	290	-	$\text{pF}$

### Source-Drain Diode

Symbol	Parameter	Test Conditions	Min.	Typ.	Max.	Units
$V_{\text{SD}}$	Forward On Voltage <sup>2</sup>	$I_{\text{S}}=-20\text{A}, V_{\text{GS}}=0\text{V}$	-	-	-1.2	V
$t_{\text{rr}}$	Reverse Recovery Time	$I_{\text{S}}=-20\text{A}, V_{\text{GS}}=0\text{V},$ $dI/dt=-100\text{A}/\mu\text{s}$	-	31	-	ns
$Q_{\text{rr}}$	Reverse Recovery Charge		-	26	-	nC

### Notes:

- 1.Pulse width limited by Max. junction temperature.
- 2.Pulse test
- 3.Surface mounted on 1 in<sup>2</sup> copper pad of FR4 board


THIS PRODUCT IS SENSITIVE TO ELECTROSTATIC DISCHARGE, PLEASE HANDLE WITH CAUTION.

USE OF THIS PRODUCT AS A CRITICAL COMPONENT IN LIFE SUPPORT OR OTHER SIMILAR SYSTEMS IS NOT AUTHORIZED.


XSEMI DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT

DESCRIBED HEREIN; NEITHER DOES IT CONVEY ANY LICENSE UNDER ITS PATENT RIGHTS, NOR THE RIGHTS OF OTHERS.


XSEMI RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION OR DESIGN.




**Fig 1. Typical Output Characteristics**




**Fig 2. Typical Output Characteristics**




**Fig 3. On-Resistance v.s. Gate Voltage**




**Fig 4. Normalized On-Resistance v.s. Junction Temperature**




**Fig 5. Forward Characteristic of Reverse Diode**




**Fig 6. Gate Threshold Voltage v.s. Junction Temperature**




**Fig 7. Gate Charge Characteristics**




**Fig 8. Typical Capacitance Characteristics**




**Fig 9. Maximum Safe Operating Area**




**Fig 10. Effective Transient Thermal Impedance**



**Fig 11. Switching Time Waveform**



**Fig 12. Gate Charge Waveform**

**MARKING INFORMATION****TO-252**

# Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

[Xsemi](#):

[XP9561GH](#)